

# AF09 ... AF38 3-pole contactors

## 5 to 20 hp at 480 V AC

### AC / DC operated

2



AF09-30-10



AF26-30-00

#### Description

AF09 ... AF38 contactors are mainly used for controlling 3-phase motors and power circuits up to 690 V AC and 220 V DC. These contactors are of the block type design with 3 main poles.

- control circuit: AC or DC operated with electronic coil interface accepting a wide control voltage range (e.g. 100...250 V AC and DC), only 4 control voltage ranges covering 24...500V 50/60 Hz and 20...500 V DC
- can manage large control voltage variations
- reduced panel energy consumption
- very distinct closing and opening.
- built-in surge suppression
- add-on auxiliary contact blocks for front or side mounting and a wide range of accessories.

#### Ordering details

IEC		UL/CSA		Rated control circuit voltage		Auxiliary contacts fitted	Catalog number	Global reference code	Weight	
Rated operational power	current $\theta \leq 40^\circ\text{C}$	3-phase motor rating 480 V	General use rating 600 V AC	Uc min. ...	Uc max.					Pkg (1 pce)
400 V AC-3	AC-1	hp	A	V 50/60 Hz	V DC				kg	
4	25	5	25	24...60	-	(1)	1 0	AF09-30-10-41	1SBL137001R4110	0.270
							0 1	AF09-30-01-41	1SBL137001R4101	0.270
							1 0	AF09-30-10-12	1SBL137001R1210	0.270
							0 1	AF09-30-01-12	1SBL137001R1201	0.270
							1 0	AF09-30-10-13	1SBL137001R1310	0.270
							0 1	AF09-30-01-13	1SBL137001R1301	0.270
							1 0	AF09-30-10-14	1SBL137001R1410	0.310
							0 1	AF09-30-01-14	1SBL137001R1401	0.310
							1 0	AF12-30-10-41	1SBL157001R4110	0.270
							0 1	AF12-30-01-41	1SBL157001R4101	0.270
							1 0	AF12-30-10-12	1SBL157001R1210	0.270
							0 1	AF12-30-01-12	1SBL157001R1201	0.270
5.5	28	7.5	28	24...60	-	(1)	1 0	AF12-30-10-41	1SBL157001R4110	0.270
							0 1	AF12-30-01-41	1SBL157001R4101	0.270
							1 0	AF12-30-10-12	1SBL157001R1210	0.270
							0 1	AF12-30-01-12	1SBL157001R1201	0.270
							1 0	AF12-30-10-13	1SBL157001R1310	0.270
							0 1	AF12-30-01-13	1SBL157001R1301	0.270
							1 0	AF12-30-10-14	1SBL157001R1410	0.310
							0 1	AF12-30-01-14	1SBL157001R1401	0.310
							1 0	AF16-30-10-41	1SBL177001R4110	0.270
							0 1	AF16-30-01-41	1SBL177001R4101	0.270
							1 0	AF16-30-10-12	1SBL177001R1210	0.270
							0 1	AF16-30-01-12	1SBL177001R1201	0.270
7.5	30	10	30	24...60	-	(1)	1 0	AF16-30-10-41	1SBL177001R4110	0.270
							0 1	AF16-30-01-41	1SBL177001R4101	0.270
							1 0	AF16-30-10-12	1SBL177001R1210	0.270
							0 1	AF16-30-01-12	1SBL177001R1201	0.270
							1 0	AF16-30-10-13	1SBL177001R1310	0.270
							0 1	AF16-30-01-13	1SBL177001R1301	0.270
							1 0	AF16-30-10-14	1SBL177001R1410	0.310
							0 1	AF16-30-01-14	1SBL177001R1401	0.310
							1 0	AF26-30-00-41	1SBL237001R4100	0.310
							0 0	AF26-30-00-12	1SBL237001R1200	0.310
							0 0	AF26-30-00-13	1SBL237001R1300	0.310
							0 0	AF26-30-00-14	1SBL237001R1400	0.350
15	50	20	50	24...60	-	(1)	0 0	AF30-30-00-41	1SBL277001R4100	0.310
							0 0	AF30-30-00-12	1SBL277001R1200	0.310
							0 0	AF30-30-00-13	1SBL277001R1300	0.310
							0 0	AF30-30-00-14	1SBL277001R1400	0.350
							0 0	AF38-30-00-41	1SBL297001R4100	0.310
							0 0	AF38-30-00-12	1SBL297001R1200	0.310
18.5	50	20	50	24...60	-	(1)	0 0	AF38-30-00-41	1SBL297001R4100	0.310
							0 0	AF38-30-00-12	1SBL297001R1200	0.310
							0 0	AF38-30-00-13	1SBL297001R1300	0.310
							0 0	AF38-30-00-14	1SBL297001R1400	0.350
							0 0	AF38-30-00-41	1SBL297001R4100	0.310
							0 0	AF38-30-00-12	1SBL297001R1200	0.310

(1) For 24...60 V 50/60 Hz - 20...60 V DC, use AF..-30-..-11 (see voltage code table). AF..-30-..-11 not suitable for direct control by PLC-output.

#### Main dimensions mm, inches

